

FADINI DIVO

PROGRAMMING INSTRUCTIONS



This remote brings two Fadini Rolling Code Series into one remote - Use as either a Jubi or Astro.
This remote can clone from Astro if using Dip-switch coding however cannot be paired directly to the receiver.

To check which remote the Divo is set to hold down buttons 3 and 4 on your new remote.



Jubi
3 Flashes



Astro
1 Flash

Swapping between Jubi and Astro

Hold down button 1 and 4 for 5 seconds, Remote will flash to confirm the new mode

Remote to Remote Cloning

New Remote: Hold down button 1 and press button 2, twice.

Release all buttons, remote LED will flash 3 times to confirm in Cloning mode. LED will remain solid

Old Remote: Press Button that Activates your device. LED will flash 3 times.

Remote to Receiver Coding

Note: This process will not work if you are using an Astro remote in fixed dip-switch coding.

Opener: Find program button on control board/receiver, Press for 2 seconds (do not hold for longer as 5+ seconds will clear your memory).

New Remote: Press button on remote you wish to program to the opener.



Warning: This product may contain a pre-installed Lithium Coin Battery. Please keep product and batteries out of reach of children. Please see [button battery safety information](#) from the Australian Competition & Consumer Commission (ACCC) for more information.